

HeadZone Care Instructions.

Whilst we strive to ensure the design and manufacture of HeadZone products is of the highest standard, some maintenance is still required to ensure long trouble-free operation. Please follow these simple steps to help maintain your equipment in good condition. Failure to carry out maintenance may void warranty.

Handheld Radio; These are NOT waterproof, so we recommend keeping them dry at all times. If using a waterproof bag such as AquaPac or Paqua, we suggest using a silica gel pack to absorb excess moisture and prevent condensation within the bag. These can be purchased separately from HeadZone or other suppliers and in some versions change colour when expired. If used in salt-air environments a light smear of petroleum jelly on all battery and radio contacts can prevent corrosion and poor contact.

RTC; Simple maintenance carried out at the end of every day's use will help prevent any build up of salt and dirt deposits which may cause poor product life.

1. Rinse helmet thoroughly in clean fresh water to remove any salt and dirt.
2. Dry helmet as best as possible.
3. Blow any excess water from the charging sockets.
4. Spray charging sockets with water displacer such as Inox, WD40 or CRC.
5. Ensure helmet is completely dry before charging.

Tips; The handheld radios and helmets can be left on charge until required as they will only trickle-charge once regular charging is completed. If using a waterproof bag, application of a thin smear of petroleum jelly to the opening will help prevent water ingress. Whilst not in use do not store the radios or helmets in direct sunlight, as direct sunlight will gradually fade the LCD and damage the finish of the helmet. Ensuring that all salt deposits are removed from the helmets will help prolong the life of the helmet lining (similar to wetsuit care).